

OPTOELECTRONIC DEVICE CAPABLE OF PARTICIPATING IN IN-BAND TRAFFIC

5

The present application claims priority under 35 U.S.C. § 119(e) to United States provisional patent application Serial No. 60/323,394, filed September 17, 2001.

10

BRIEF DESCRIPTION OF THE INVENTION

The present invention relates generally to optoelectronic devices. More particularly, the present invention relates to an optoelectronic transceiver, transmitter or receiver having a network address and capable of participating in in-band traffic.

15

BACKGROUND OF THE INVENTION

Fig. 1 shows a schematic representation of the essential features of a typical prior-art fiber optic transceiver. The main circuit 1 contains at a minimum transmit and receiver circuit paths and power 19 and ground connections 18. The receiver circuit typically consists of a Receiver Optical Subassembly (ROSA) 2 which contains a mechanical fiber receptacle as well as a photodiode and pre-amplifier (preamp) circuit. The ROSA is in turn connected to a post-amplifier (postamp) integrated circuit 4, the function of which is to generate a fixed amplitude digital signal that is connected to outside circuitry via the RX+ and RX- pins 17. The postamp circuit also often provides a digital output signal known as Signal Detect or Loss of Signal indicating the presence or absence of suitably strong optical input. The Signal Detect output is provided as an output on pin 20. The transmit circuit will typically consist of a Transmitter Optical Subassembly (TOSA) 3 and a laser driver integrated circuit 5. The TOSA contains a mechanical fiber receptacle as well as a laser diode or LED. The laser driver circuit 5 will typically provide AC drive and DC bias current to the laser. The signal inputs for the driver are obtained from the TX+ and TX- pins 12. Typically, the laser driver circuitry will require individual factory setup of certain parameters such as the bias current (or output power) level and AC modulation drive to the laser. Typically, this is accomplished by adjusting variable resistors or placing factory selected resistors 7, 9 (i.e., having factory selected resistance values). Additionally, temperature compensation of the bias current and modulation is often required. This function can be integrated in the laser driver integrated circuit or accomplished through the use of external temperature sensitive elements such as thermistors 6, 8.

The TX disable pin 13 allows the transmitter to be shut off by the host device, while the TX fault pin 14 is an indicator to the host device of some fault condition existing in the laser or associated laser driver circuit. In addition, the optoelectronic device 1 may include an optional eye-safety integrated circuit 11 that performs functions aimed at preventing non-eyesafe emission levels when a fault condition exists in the laser circuit. Also shown in Fig. 1 is an EEPROM 10 for storing standardized serial ID information that can be read out via a serial interface (e.g., using the serial interface of the ATMEL AT24C01A family of EEPROM products) consisting of a clock 15 and data 16 line.

The signal pins described above collectively provide an electrical interface between the optoelectronic device 1 and the host device. The optoelectronic transceiver industry over the years has standardized one such interface, known as the GBIC standard. An advantage of the GBIC standard is its relative simplicity and the low production cost of the integrated circuits required for implementation. Another advantage is that the size of the transceiver can be quite compact.

One disadvantage of the GBIC standard, however, is that the transceiver is reliant on the host device to perform a variety of operations such as reset and shutdown. If the host device malfunctions, the transceiver attached to it may not be able to perform these operations properly. Another disadvantage of the GBIC standard is its inflexibility. It is difficult to implement functionality in addition to those described in the GBIC standard.

Accordingly, there is a need for a highly flexible interface between an optoelectronic device and a host device.

SUMMARY OF THE INVENTION

An embodiment of the present invention is an optoelectronic device that has an assigned network address (e.g., Internet Protocol address) and participates in in-band traffic for purposes of performing functions (e.g., network diagnostics, network control, network provisioning, fault isolation, etc.) that are traditionally performed by host equipment. An optoelectronic device can be an optoelectronic transceiver, an optoelectronic transmitter, or an optoelectronic receiver.

In one embodiment, the optoelectronic device includes a protocol engine and a status monitoring module. The protocol engine identifies data packets that are addressed to the optoelectronic device, and allows the optoelectronic device to insert packets of information generated by the device into in-band data. Logic of the optoelectronic device may modify

the operating parameters of the device according to the control information included in the data packets. The status monitoring module detects the device's physical conditions and the conditions of its links. Status information generated by the status monitoring module may be incorporated into the in-band data by the protocol engine such that the status information may be communicated to a host device or a remote device. The protocol engine is programmable to communicate in various network protocols and to perform a variety of operations. Thus, additional functionality may be added to the optoelectronic device without altering the interface through which the device communicates with the host.

In one embodiment, the optoelectronic device includes an input/output (I/O) interface for coupling to a host device, and an optical output interface for coupling to an optical medium, such as an optical fiber. Through the I/O interface, the optoelectronic device may receive a stream of data that includes data packets. Some of the data packets may have destination addresses matching the predefined address assigned to the optoelectronic device. Circuits of the optoelectronic device identify such data packets and process the information (data and/or commands) included in the identified data packets. The identified data packets may be removed from the data stream before the data stream is converted into optical signals. The optoelectronic device may also include an optional local module I/O interface through which the device can communicate with the host or with another optoelectronic device coupled to the host.

The optoelectronic device may include an optical input interface. Through the optical input interface, the optoelectronic device is configured for receiving a data stream that includes data packets, some of which may be addressed to the optoelectronic device. Circuits of the optoelectronic device identify such data packets and process the information included in the identified data packets. The optoelectronic device may remove the identified data packets from the data stream before the data stream is communicated to the host device.

The optoelectronic device may generate new data packets in response to information included in the identified data packets, or in response to the occurrence of a predefined event. The new data packets may also be generated periodically. The new data packets may be communicated to the host device via the input/output interface, or to a remote device whose address is defined by the identified data packets via a computer network. In other embodiments, the optoelectronic device may be configured to send the new data packets to any predefined device or devices via a network.

The status monitoring module may include sensors for detecting the physical conditions of the optoelectronic device and/or the conditions of the optical medium. The detected information may be incorporated into data packets generated by the protocol engine. The data packets generated by the protocol engine may be addressed to the host device and/or to any device coupled to the optoelectronic device via a network. In this way, the optoelectronic device is capable of reporting its conditions and/or the conditions of its optical links to the host computer or to any remote device in the network.

BRIEF DESCRIPTION OF THE DRAWINGS

For a better understanding of the invention, reference should be made to the following detailed description taken in conjunction with the accompanying drawings, in which:

Fig. 1 is a block diagram depicting a prior-art optoelectronic transceiver.

Fig. 2A is a block diagram depicting an optoelectronic transceiver in accordance with one embodiment of the present invention.

Fig. 2B is a block diagram depicting an optoelectronic transceiver in accordance with another embodiment of the present invention.

Fig. 3A is a block diagram depicting an implementation of a protocol engine according to one embodiment of the present invention.

Fig. 3B is a block diagram depicting an implementation of a protocol engine according to another embodiment of the present invention.

Fig. 4 is a block diagram depicting an implementation of the extractor circuit of Fig. 3.

Fig. 5 is a block diagram depicting an implementation of the merge circuit of Fig. 3.

Fig. 6 is a block diagram depicting a network having fiber optic transceivers remotely coupled to a controller system and a database that stores relevant information of the transceivers.

Fig. 7A depicts a top view of an optoelectronic device in accordance with an embodiment of the present invention.

Fig. 7B depicts a side view of the optoelectronic device of Fig. 7A.

Fig. 8 is a block diagram illustrating a host device that has two optoelectronic transceivers that are capable of communication with each other via a local I/O interface in furtherance of an embodiment of the invention.

Fig. 9 is a block diagram depicting an optoelectronic transmitter in accordance with another embodiment of the invention.

Fig. 10 is a block diagram depicting an optoelectronic receiver in accordance with another embodiment of the invention.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Fig. 2A shows a schematic representation of a fiber optic transceiver 100 in accordance with an embodiment of the present invention. Transceiver 100 includes a Receiver Optical Subassembly (ROSA) 102, which contains a mechanical fiber receptacle as well as a photodiode and a pre-amplifier (preamp) circuit. ROSA 102 is in turn connected to a post-amplifier (postamp) integrated circuit 104, the function of which is to take relatively small signals from ROSA 102 and amplify and limit them to create a uniform amplitude digital electronic output. The postamp circuit 104 provides a digital output signal known as Signal Detect or Loss of Signal indicating the presence or absence of suitably strong optical input.

The transmit circuitry of transceiver 100 consists of a Transmitter Optical Subassembly (TOSA) 103 and a laser driver integrated circuit 105. TOSA 103 contains a mechanical fiber receptacle as well as a laser diode or LED. Laser driver circuit 105 provides AC drive and DC bias current to the laser. The signal inputs for the driver are obtained from I/O pins (not shown) of transceiver 100.

SERDES (SERializing and DESerializing) circuits are incorporated within the transceiver 100. SERDES circuits serve the function of converting parallel data to serial data and vice versa. In the illustrated embodiment, ROSA 102 is coupled to SERDES circuitry that includes framing and serial-to-parallel converter circuits 110 and clock recovery circuit 112. TOSA 103 is coupled to SERDES circuitry that includes parallel-to-serial converter circuit 120 and high-speed clock synthesizer circuit 122.

Also contained in transceiver 100 is control circuitry 150, which may include one or more integrated circuits configured for controlling the operations of the transceiver 100. Control circuitry 150 is coupled to provide control signals to ROSA 102, TOSA 103, post-amplifier 104, and laser driver 105, while these components provide feedback signals back to control circuitry 150. For example, control circuitry 150 provides signals to control the bias current level and AC modulation of laser driver circuit 105, while post-amplifier circuit 104 provides a Signal Detect output to control circuitry 150 to indicate the presence or absence of a suitably strong optical input. Other control functions, such as temperature compensation of laser driver circuit 105, may also be carried out by the control circuitry 150. Temperature and/or other physical conditions of various components of transceiver 100 may be acquired using sensors 160 that are coupled to control circuitry 150. In some embodiments, conditions of the optical links may be also be acquired using sensors 160. In

some embodiments, the control circuitry may include one or more programmable microcontrollers and/or microprocessors.

In addition to, and sometimes in conjunction with these basic control functions, there are a number of other tasks that may be handled by control circuitry 150. These tasks include, but are not necessarily limited to, the following:

- Setup functions. These generally relate to the required adjustments made on a part-to-part basis in the factory to allow for variations in component characteristics such as laser diode threshold current.
- Identification. This refers to the storage of an identity code within a general purpose memory (e.g., an EEPROM). In a preferred embodiment of the present invention, the identity code is stored in the form of an IP (Internet Protocol) address. Additional information, such as sub-component revisions and factory test data, may also be stored within the general purpose memory for purposes of identification.
- Eye safety and general fault detection. These functions are used to identify abnormal and potentially unsafe operating parameters and to report these to the user and/or perform laser shutdown, as appropriate. Sensors 160 may be used to identify such abnormal or potentially unsafe operating parameters.
- Receiver input optical power measurement. This function is used to measure the input optical power such that a suitable signal amplification level can be set.
- Laser diode drive current. This function is used to set the output optical power level of the laser diode.
- Laser diode wavelength control. This function is used to set the wavelength of light emitted by the laser diode. This feature is critical in Dense Wave Division Multiplexing (DWDM) systems. The wavelength of the light emitted by the laser diode, in some embodiments, may be changed by adjusting the temperature of the laser diode.
- Laser diode temperature monitoring and control. In one embodiment, an optional temperature controller (e.g., a thermal-electric cooler) may be disposed in or near TOSA 103 for controlling the temperature of the laser diode. In that embodiment, control circuitry 150 is also responsible for providing control signals to the temperature controller.

Note that transceiver 100 is configured for coupling to a host device. As used herein, a host device refers to a link card to which a transceiver is attached and/or a host system computer to which a transceiver provides an optical connection. Host systems may be computer systems, network attached storage (NAS) devices, storage area network (SAN) devices, optoelectronic routers, as well as other types of host systems and devices. Transceiver 100 can be attached to a host device through a serial interface.

With reference still to Fig. 2A, control circuitry 150 is configured to receive de-serialized data from serial-to-parallel converter circuit 110. The de-serialized data are processed by control circuitry 150 before they are converted into serial data and transmitted to the host device. Specifically, control circuitry 150 monitors the stream of data that it receives from serial-to-parallel converter circuit 110 (an “inbound” data stream) and determines whether the data contains any information intended to be communicated to the transceiver 100. If such information is identified, control circuitry 150 retrieves the information from the “inbound” data stream and performs operations according to the identified information. In response to the identified information, control circuitry 150 may modify the “inbound” data stream by removing the identified data packets and/or by inserting new data packets in the data stream.

In this document, the term “data packet” is used broadly to mean all packets of information transmitted over a data path. Thus, “data packets” includes protocol packets, packets having only command information, and the like, as well as packets containing data being transmitted over a data channel.

For the purposes of illustration, assume that transceiver 100 is assigned an IP address, and transceiver 100 is configured for coupling to an IP network. The data stream that passes through control circuitry 150 will include data packets each having a packet header and a destination address. Data packets having a destination address matching the IP address assigned to transceiver 100 are retrieved from the data stream by control circuitry 150. These data packets may include, within their payload portions, commands to report the transceiver’s current status information to the host device or to a specific IP address, for example. In another example, these data packets may include commands to adjust the bias level of laser driver 105, or adjust the wavelength of the emitted light. Control circuitry 150, upon processing these data packets, will perform the indicated operations. Data packets that are not addressed to transceiver 100 will pass through unmodified.

In some embodiments of the invention, the control circuitry 150 is configured to receive an “outbound” data stream from the host device. In this embodiment, “outbound” serial data from the host device are de-serialized by SERDES circuits before they are transmitted to the control circuitry 150. Control circuitry 150 monitors the de-serialized “outbound” data stream and determines whether the data stream contains any information intended to be communicated to the transceiver. If such information is identified, control circuitry 150 retrieves the information from the “outbound” data stream and performs operations according to the identified information. In response to the identified

information, control circuitry may modify the “outbound” data stream by removing the identified data packets and/or by inserting new data packets in the data stream. The “outbound” data stream is then provided to parallel-to-serial converter circuit 120 to be serialized and subsequently converted to optical signals by TOSA 103.

In some embodiments of the present invention, control circuitry 150 is configured to process both “inbound” and “outbound” data streams. In these embodiments, information from one data stream may effect modification of another data stream. For example, from the “outbound” data stream, the transceiver may receive a command to report its operating parameters to the host device. In that event, the transceiver may generate a data packet containing its operating parameters and send the data packet to the host device via the “inbound” data stream. In another example, the transceiver may receive from the “inbound” data stream a command to report its operating parameter to a specified network address. In that event, the transceiver may generate a data packet containing its operating parameters and send the data packet to the specified network address via the “outbound” data stream.

In furtherance of the present invention, transceiver 100 may generate data packets to be communicated to the host device or to a remote device upon the occurrence of a predefined event. For example, when sensors 160 detect an unsafe operating condition, transceiver 100 may attempt an emergency shut down. In that event, transceiver 100 may generate data packet(s) indicating the shut down and send the data packet(s) to the host device and/or a remote device via another network connection of the host. In another example, when sensors 160 detect that the wavelength of light emitted by the laser diode of TOSA 103 has deviated significantly, transceiver 100 may generate a data packet containing a warning signal to the host device or a remote device via another network connection of the host device. In yet another example, when sensors 160 detect that a laser diode of TOSA 103 is exhibiting symptoms known to be predictive of future failure of the laser diode, transceiver 100 may generate a data packet indicating the condition of the laser diode and send the information to the host device and/or remote device. In some embodiments, transceiver 100 may be configured to send data packets containing status information to the host device and/or a specified remote device periodically. In another embodiment, the transceiver 100 may be programmed to send an electronic message (e-mail) to a particular IP address upon encountering an error condition.

In accordance with one embodiment of the invention, transceiver 100 does not communicate exclusively using data packets. Also shown in Fig. 2A is an optional local module input/output (I/O) interface through which the transceiver may communicate with

the host device. In this embodiment, transceiver 100 may be configured to transmit its status information (e.g., information generated by sensors 160, Loss of Signal, etc.) and network address to the host device via the local module I/O interface such that the host device can forward the information to another address via the host device's other network connections. Communication via the local I/O module can be used for reporting link failures. For instance, if the optical link coupled to transceiver 100 is interrupted, transceiver 100 may communicate the link's condition and its network address to host device. The host may then forward the link's condition to the network administrator, the party who is responsible for maintaining the link, or a centralized network control system.

Using the local module I/O interface, transceiver 100 can serve as a conduit of information for all optoelectronic devices within the same host. Fig. 8 is a block diagram illustrating such a configuration. As shown in Fig. 8, a host device 800 with two transceivers Transceiver A and Transceiver B coupled thereto includes a local module I/O bus 810 for allowing Transceiver A to communicate with Transceiver B via the local module I/O interface. Status information of Transceiver B may be communicated to Transceiver A via the local module I/O interface such that the status information can be communicated to the host device or a remotely coupled device via in-band data of Transceiver A.

Furthermore, Transceiver A can be a transceiver capable of participating in in-band data communication (e.g., transceiver 100), and Transceiver B may be a transceiver that is not capable of participating in in-band data communication. Multiple transceivers that are not capable of participating in in-band data communication by themselves may be coupled to the host device and may participate in in-band communication through Transceiver A as long as these transceivers are capable of communicating via the local module I/O interface.

Fig. 6 is a block diagram illustrating a control system 600 coupled to receive status information of multiple transceivers 610 to which the control system 600 is remotely coupled via a packet-switched network 690. Transceivers 610 have IP addresses different from those of their associated host devices 620. The IP addresses of transceivers 610 are stored within a database 605 of the control system 600. The control system 600 may periodically send status update requests to the transceivers 610 in data packets addressed to transceivers 610. The status update requests may include the IP address of the control system 600. Thus, upon receiving the status update requests, the transceivers 610 may respond by sending their status information to the control system 600. A centralized

database of transceiver status information may then be maintained by the control system 600.

In furtherance of the present invention, control system 600 may remotely control the operation parameters of transceivers 610. This feature is useful for system administration and enables remote trouble-shooting of transceiver problems. This feature is also useful for centralized control of network parameters and resources, such as transmission wavelengths in a DWDM system.

Attention now turns to implementation of control circuitry 150. Fig. 3A is a block diagram depicting portions of control circuitry 150 in accordance with one implementation of the present invention. Particularly, a protocol engine 350 that includes an address memory 210, an extractor 212, a merge circuit 214, an IN buffer 216, an OUT buffer 218, a merge controller 220, an instruction and program memory 222, a processor 224, and a sensor data storage 226, is illustrated.

Address memory 210, which may be an EEPROM (Electrically Erasable and Programmable Read Only Memory) or any type of non-volatile memory, stores a network address of the transceiver. The extractor 212 receives a stream of data packets and compares the network address of the transceiver with destination addresses of the data packets received. If there is a match, extractor 212 extracts the matching data packets from the data stream, and stores the extracted data packets within the IN buffer 216. The remaining data packets, which do not have a destination address matching the network address of the transceiver, are passed to merge circuit 214.

Instruction and program memory 222 contains programs and/or instructions, for execution by the processor 224, for decoding and processing data packets addressed to the transceiver, for analyzing data received from the sensors 160, for modifying the operational state of the transceiver (e.g., by modifying the bias applied to the laser diode by laser driver, and/or by activating and deactivating various circuits within the transceiver), and for generating new data packets addressed to the host device or other network device. In one embodiment of the invention, these programs and instructions contained in memory 222 may be modified by the user(s) such that the optoelectronic device may be reprogrammed to communicate in various network protocols and to perform a variety of operations. By altering the program codes contained in memory 222, additional functionality may be added to the optoelectronic device without altering the interface through which it communicates with the host.

With reference still to Fig. 3A, data packets extracted by the extractor 212 are replaced with link idle symbols at the output so that the link is kept active and error free. The extracted data packets are processed by processor 224 in accordance with the program codes stored within memory 220 and/or operational state(s) of the device. In the present embodiment, processor 224 may process the information contained in the data packets in conjunction with instructions stored within instruction and program memory 222 and/or sensor data stored within sensor data storage 226. For example, the extracted data packets may contain an instruction that calls for an operation defined by the program codes stored within the instruction and program memory 222. In another example, the extracted data packets may contain an instruction that instructs the transceiver to obtain sensor data from sensor data storage 226, generate a status report of its current operating conditions and transmit the status report to a specified network address. In yet another example, the extracted data packets may contain new processor instructions to be stored within instructions and program memory 222.

Data packets generated by processor 224 are temporarily stored within OUT buffer 218. Merge circuit 214, under the control of merge circuit controller 220, merges the processor-generated data packets with data packets that are not addressed to the transceiver to form a modified data stream. If processor 224 does not generate any new data packets, the merge circuit forms a modified data stream with the data packets that are not addressed to the transceiver. In the present embodiment, the merge circuit 214 inserts processor-generated data packets into other data packets by monitoring the data stream and replacing a protocol suitable number of link idle symbols with the processor-generated data packets.

Observe that protocol engine 350 of Fig. 3A is configured for processing and modifying one data stream. A fiber optic transmitter or receiver having a single datapath may implement the circuitry of Fig. 3A. A fiber optic transceiver having multiple datapaths may implement one or more instances of the protocol engine 350.

Fig. 3B is a block diagram depicting an implementation of a protocol engine 350' for a fiber optic transceiver having two data paths. The control circuitry is configured for processing and modifying more than one data stream. In addition to the control circuitry shown in Fig. 3A, the protocol engine embodiment of Fig. 3B includes a second extractor 232, IN buffer 236, OUT buffer 238 and merge circuit 240. The first set of circuits (212, 214, 216, 218, 220) are used with a first data path (e.g., the inbound data path), while the second set of circuits (232, 234, 236, 238, 240) are used with a second data path (e.g., the outbound data path). Data packets with a destination address matching the network address

of the transceiver are extracted from the data streams and processed by processor 224. Data packets generated by processor 224 may be inserted in any one of the data streams, depending on the intended destination of the processor-generated packets. In this way, a response triggered by a data packet sent by the host device can be directed back to the host device quickly.

Fig. 4 is a block diagram depicting an implementation of an extractor circuit 212 in accordance with one embodiment of the present invention. Extractor circuit 212 consists of a FIFO (First In First Out buffer) 310, a demultiplexer (demux) 312, a comparator 314, and extractor control logic 316. FIFO 310 is configured to receive and temporarily store a stream of data packets. While the data packets are progressing through FIFO 310, a comparator examines the destination address bits of each packet, and compares the destination address of each packet with the network address of the transceiver. If a match is found, comparator 314 triggers extractor control logic 316 to send an appropriate signal to the demux 312 such that the matching data packet is diverted to the IN buffer 216. The non-matching data packets are provided to demux 312 to be passed onto merge circuit 214.

The comparator 314 also detects the end of each packet and sends an EOF signal to the extractor control logic 316 when the end of a packet has been conveyed to the IN buffer 216. This helps the extractor control logic 316 to control the diversion of variable length packets to the IN buffer 216, by enabling it to know when the end of such packets have been fully transferred from the FIFO 310 to the IN buffer 216. In an alternate embodiment, all packets addressed to the transceiver (i.e., having a destination address matching the address assigned to the transceiver) are fixed length packets, thereby eliminating the need for end of packet detection circuitry in the comparator 314. In yet another alternate embodiment, the length of each packet addressed to the transceiver is specified in the header of the packet and that length information is extracted (e.g., by the comparator 314 or a parallel circuit) and conveyed to the extractor control logic 316 to enable it to handle the transfer of variable size data packets from the FIFO 310 to the IN buffer 216.

Fig. 5 is a block diagram depicting an implementation of a merge circuit 214 and merge controller logic 220 in accordance with one embodiment of the present invention. Merge circuit 214 consists of FIFO buffers 510, 520 and a multiplexer (mux) 530. FIFO 510 receives a data stream from extractor circuit 510, and FIFO 520 receives a data stream from OUT buffer 218. As mentioned, data contained in OUT buffer 218 are generated by processor 224. The FIFO1 and FIFO2 buffers 510, 520 include circuitry for generating fullness indication signals Fullness1 and Fullness2, respectively, which indicate the fullness

of these buffers. The Fullness2 signal indicates when a full packet from the processor 214 (see Figs. 3A, 3B) is present in FIFO2. The Fullness1 signal indicates when FIFO1 contains less than a threshold level of data. For example, Fullness1 may indicate when FIFO1 is at least half empty. Alternately, Fullness1 may indicate when FIFO1 is sufficiently empty to enable transmission of a full data packet from FIFO2 without risking overflow of FIFO1 by new incoming data. In this regard, it is noted that “filler” signals, sometimes called “idles” or “null data signals,” are transmitted on the data paths between data packets, but are not stored in the FIFO’s of the transceiver. When data packets are transmitted at less than the maximum transmission rate of the data channel, the FIFO’s in the data path become partially or even completely empty.

A first comparator 522 sends an EOF1 signal to the merge control logic 316 when the end of packet is transferred from FIFO1 to the Mux 530, and a second comparator 524 sends an EOF2 signal to the merge control logic 316 when the end of packet is transferred from FIFO2 to the Mux 530. Mux 530 selectively outputs data from either FIFO 510 or FIFO 520, depending on the SRC_Select signal generated by merge controller logic 220, which generates the SRC_Select signal based in part on the Fullness1 and Fullness2 signals from the FIFO’s 510, 520. When both FIFO1 and FIFO2 are empty, Mux 530 generates and outputs filler signals (e.g., idles) to the output data stream.

In addition to generating the SRC_Select signal, merge controller logic 220 generates clock signals ReadClk1 and ReadClk2 for controlling the outflow of data from FIFO 510 and FIFO 520. In particular, when the Fullness2 signal indicates that a full packet (produced by the data processor 224, Fig. 3A or 3B) is ready for transmission, the Fullness1 signal indicates that FIFO1 is less full than the predefined threshold, and the EOF signal from comparator 522 indicates that the last symbol transferred from FIFO1 to the Mux 530 was the end of a data packet, then the merge control logic 316 stops the outflow of data from FIFO1 (by deactivating ReadClk1) and enables the outflow of data from FIFO2 (by activating ReadClk2) until a full data packet is transferred from FIFO2 to the Mux 530. When a full data packet has been transferred from FIFO2 to the Mux 530, as indicated by the EOF2 signal, the merge control logic 316 determines whether to next send a data packet from FIFO1 or FIFO2 based on the current status of the Fullness1 and Fullness2 signals. When both FIFO1 and FIFO2 are empty, a filler signal is sent from either FIFO to the Mux 530, thereby causing the Mux 530 to transmit filler signals until such time that it receives a new data packet from either of the FIFO’s.

Figs. 7A and 7B illustrate the dimensions of an optoelectronic device 700 that may be constructed in accordance with embodiments of the present invention. Fig. 7A shows a top view of the optoelectronic device 700, and Fig. 7B shows a side view. The physical dimensions of the optoelectronic device 700 are as follows: width, 3 cm or less; length, 6.5 cm or less, and height, 1 cm or less. In an alternate embodiment, the physical dimensions of the optoelectronic device 700 are: width, 0.54 inches or less; length, 2.24 inches or less; and height, 0.34 inches or less. Optoelectronic device 700 includes an electrical interface 702 for coupling to a host device and a circuit board 704 containing SERDES circuits (e.g., clock recovery circuit 112, framing and serial-to-parallel circuit 110, high-speed clock synthesizer circuit 122, parallel-to-serial converter circuit 120, See Fig. 2A) and control circuitry. Note that the SERDES circuits and the control circuit 150 including processors, A/D converters, D/A converters, protocol processing circuits, FIFOs, program memories, etc., may be implemented as a single integrated circuit. Coupled to the circuit board 704 are optical subassemblies 706 (e.g., ROSA 102 and TOSA 103) and the optical connectors 710 for coupling to fiber optic cables.

Attention now turns to Fig. 2B, which depicts a schematic representation of a fiber optic transceiver 101 in accordance with an alternate embodiment of the present invention. Fiber optic transceiver 101 is similar to fiber optic transceiver 100. One difference, however, between transceiver 101 and transceiver 100 is that transceiver 101 is configured for coupling to the host device via a parallel interface. Thus, SERDES circuits for serializing and de-serializing data between the host device and transceiver 101 are omitted.

Some embodiments of the present invention described above include optoelectronic transceivers that have one datapath for in-bound network traffic and another datapath for out-bound network traffic. But the present invention is not limited to transceivers. Rather, embodiments of the present invention include optoelectronic transmitters and optoelectronic receivers that are capable of participating in "in-band" communication.

Fig. 9 is a block diagram depicting an optoelectronic receiver 900 in accordance with another embodiment of the invention, and Fig. 10 is a block diagram depicting an optoelectronic transmitter 910 in accordance with another embodiment of the invention. Implementation of optoelectronic receiver 900 and optoelectronic transmitter 910 is substantially similar to that of transceiver 100. A difference, however, is that transmitter 900 is not configured to receive optical signals, and that receiver 910 is not configured to transmit optical signals.

The foregoing descriptions of specific embodiments of the present invention are presented for purposes of illustration and description. They are not intended to be exhaustive or to limit the invention to the precise forms disclosed, obviously many modifications and variations are possible in view of the above teachings. The embodiments
5 were chosen and described in order to best explain the principles of the invention and its practical applications, to thereby enable others skilled in the art to best utilize the invention and various embodiments with various modifications as are suited to the particular use contemplated.

10

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
222